

## CT 6056 Charging Tray

- · Charges and stores up to 56 digital IR receivers
- · Rapidly charges batteries in under two hours without battery removal
- Durable storage case



### Description

The charging tray can recharge up to 56 receivers at once. The charging tray contains power supply with automatic mains voltage selection. The charging electronics and a charging indicator LED are included in each receiver. The charging circuitry checks to see if a battery pack is present and controls the charging process.

The charging process takes approximately one hour and 45 minutes with the BP 6001 Battery Pack.

### Features

The CT 6056 has the following standard features:

- · Chargers up 56 receivers at once
- · Charges batteries to full in under two hours
- · Rugged and durable road case
- · Internal power supply with automatic mains voltage selection
- · Standby mode for reduced power consumption

## Specifications

# How To Order

Charging tray for 56 pieces DR 60xx digital receivers CT 6056

#### Electrical

Mains Voltage	65 Hz to 16kHz
Power Consumption	Operation: 270 W (charging 56 receivers) Standby: 7 W (no receivers in the charging unit)
Mechanical	
Dimensions (W x H x D)	130 x 680 x 520 mm
Color	Black
Weight	With 56 receivers: 18 kg Empty: 11.2 kg

Transport: -40 to +70°C (-40 - 158°F)

Operating: 5 to 45°C (41 to 113°F)

#### Certifications

The DCS 6000 system conforms to standard IEC 60914.

Temperature range



United States, Canada, Latin America, Caribbean: Shure Incorporated 5800 West Touhy Avenue Niles, IL 60714-4608 USA

Phone: +1 847-600-2000 Fax: +1 847-600-1212 (USA) Fax: +1 847-600-6446 Email: info@shure.com www.shure.com Europe, Middle East, Africa: Shure Europe GmbH Jakob-Dieffenbacher-Str. 12, 75031 Eppingen, Germany

Phone: +49-7262-92490 Fax: +49-7262-9249114 Email: info@shure.de www.shure.eu Asia, Pacific: Shure Asia Limited 22/F, 625 King's Road North Point, Island East Hong Kong

Phone: +852-2893-4290 Fax: +852-2893-4055 Email: info@shure.com.hł www.shureasia.com