


# ARTcessories™

Creative audio solutions in cool little boxes.

**JULY 2005**

## DJPRE II

Phono Preamp




The DJ PRE II is a high quality Phono preamp designed for your home and studio. It acts as an interface between your turntable and your audio recording system. The analog input capacitance can be switched between 100pf and 200pf to optimize your phono cartridge response. A switchable low cut filter removes turntable rumble while leaving the audio pristine. The front gain trim control and signal/clip LED allow you to optimize the preamps gain for a wide range of input sources. The built-in low noise Phono preamp circuitry is highly accurate and precisely conforms to the RIAA standard. The Line Output jacks are low impedance and can work with any sound card.

Housed in an all aluminum black anodized case, the DJ PRE II can be powered by a wide variety of external supplies. If you need to amplify and EQ your vinyl records to interface with your audio workstation, sound card, or main monitor system, the DJ PRE II gives you flawless audio reproduction in a rugged and reliable package.

### Specifications:

Frequency Response:	10Hz -50KHz, +/- .5dB
THD:	.01% Typical @ 1KHz
Hum and Noise:	>90dB below clipping
Input Impedance:	47k Ohms in parallel with either 100pF or 200pF
Maximum Input Level:	40mVrms @1KHz
Maximum Gain:	45dB @ 1KHz
Input / Output Connections:	RCA
Maximum Output Level:	+6dBu (1.4Vrms)
Filter Type/Response:	Switchable, Low Cut, -3dB @ 22Hz
Power Requirements:	7-12V DC or 9-12V AC @ 150mA
Dimensions:	1.75"H x 4.2"W x 3.5"D (44.5mm x 107mm x 89mm)
Weight:	1.25 lbs. (.57kg)



DESIGNED & DISTRIBUTED BY: APPLIED RESEARCH AND TECHNOLOGY  
 215 Tremont Street • Rochester, New York 14608 • USA  
 For Customer Service, please call: 585.436.2720  
 Email: support@artproaudio.com • www.artproaudio.com  
 ART-ARTcs-05/05

Designed & Developed in the US by: APPLIED RESEARCH AND TECHNOLOGY • Made in China