

Roland®

ep-760

DIGITAL PIANO

Owner's Manual	Page	1
Mode d'emploi	Page	35
Manual del Usuario	Pag.	69



This product complies with the requirements of European Directive 89/336/EEC.

For EU Countries

FEDERAL COMMUNICATIONS COMMISSION RADIO FREQUENCY INTERFERENCE STATEMENT

For the USA

This equipment has been tested and found to comply with the limits for a Class B digital device, pursuant to Part 15 of the FCC Rules. These limits are designed to provide reasonable protection against harmful interference in a residential installation. This equipment generates, uses, and can radiate radio frequency energy and, if not installed and used in accordance with the instructions, may cause harmful interference to radio communications. However, there is no guarantee that interference will not occur in a particular installation. If this equipment does cause harmful interference to radio or television reception, which can be determined by turning the equipment off and on, the user is encouraged to try to correct the interference by one or more of the following measures:

- Reorient or relocate the receiving antenna.
- Increase the separation between the equipment and receiver.
- Connect the equipment into an outlet on a circuit different from that to which the receiver is connected.
- Consult the dealer or an experienced radio/TV technician for help.

This device complies with Part 15 of the FCC Rules. Operation is subject to the following two conditions:

- (1) This device may not cause harmful interference, and
- (2) This device must accept any interference received, including interference that may cause undesired operation.

Unauthorized changes or modification to this system can void the users authority to operate this equipment.
This equipment requires shielded interface cables in order to meet FCC class B Limit.

For Canada

NOTICE

This Class B digital apparatus meets all requirements of the Canadian Interference-Causing Equipment Regulations.

AVIS

Cet appareil numérique de la classe B respecte toutes les exigences du Règlement sur le matériel brouilleur du Canada.

Roland®

ep-760 DIGITAL PIANO

Owner's Manual

Thank you, and congratulations on your choice of the Roland Digital Piano ep-760.

Main Features

Piano sounds with rich resonance and wide-ranging expressiveness

The stereo sampling piano sound generator realistically reproduces even the sound of the hammers striking the strings, producing the tones of a high-quality concert grand piano. Maximum polyphony of 64 notes ensures that you can use the pedal freely without running out of notes.

A variety of practice features to help you develop your musicality

In addition to a metronome, the ep-760 features a two-track recorder, which allows you to experience piano lessons in a way possible only on electronic pianos.

65 piano songs built-in

The built-in songs are mainly classical pieces, and include compositions for listening enjoyment as well as for lessons.

Before using this unit, carefully read the sections entitled: "Using the unit safely", p. 2 and "Important Notes", p. 4. These sections provide important information concerning the proper operation of the unit. Additionally, in order to feel assured that you have gained a good grasp of every feature provided by your new unit, the Owner's manual should be read in its entirety. The manual should be saved and kept on hand as a convenient reference.

Copyright © 2002 ROLAND CORPORATION

All rights reserved. No part of this publication may be reproduced in any form without the written permission of ROLAND CORPORATION.

USING THE UNIT SAFELY

INSTRUCTIONS FOR THE PREVENTION OF FIRE, ELECTRIC SHOCK, OR INJURY TO PERSONS

About ⚠ WARNING and ⚠ CAUTION Notices

⚠ WARNING	Used for instructions intended to alert the user to the risk of death or severe injury should the unit be used improperly.
⚠ CAUTION	Used for instructions intended to alert the user to the risk of injury or material damage should the unit be used improperly. * Material damage refers to damage or other adverse effects caused with respect to the home and all its furnishings, as well to domestic animals or pets.

About the Symbols

	The ⚠ symbol alerts the user to important instructions or warnings. The specific meaning of the symbol is determined by the design contained within the triangle. In the case of the symbol at left, it is used for general cautions, warnings, or alerts to danger.
	The ⓧ symbol alerts the user to items that must never be carried out (are forbidden). The specific thing that must not be done is indicated by the design contained within the circle. In the case of the symbol at left, it means that the unit must never be disassembled.
	The ● symbol alerts the user to things that must be carried out. The specific thing that must be done is indicated by the design contained within the circle. In the case of the symbol at left, it means that the power-cord plug must be unplugged from the outlet.

ALWAYS OBSERVE THE FOLLOWING

⚠ WARNING

- Before using this unit, make sure to read the instructions below, and the Owner's Manual.

- Do not open (or modify in any way) the unit or its AC adaptor.

- Do not attempt to repair the unit, or replace parts within it (except when this manual provides specific instructions directing you to do so). Refer all servicing to your retailer, the nearest Roland Service Center, or an authorized Roland distributor, as listed on the "Information" page.

- Never use or store the unit in places that are:
 - Subject to temperature extremes (e.g., direct sunlight in an enclosed vehicle, near a heating duct, on top of heat-generating equipment); or are
 - Damp (e.g., baths, washrooms, on wet floors); or are
 - Humid; or are
 - Exposed to rain; or are
 - Dusty; or are
 - Subject to high levels of vibration.

- Make sure you always have the unit placed so it is level and sure to remain stable. Never place it on stands that could wobble, or on inclined surfaces.

- The instrument should be connected to a power supply only of the type described in the operating instructions, or as marked on the unit.

⚠ WARNING






- Be sure to use only the AC adaptor supplied with the unit. Also, make sure the line voltage at the installation matches the input voltage specified on the AC adaptor's body. Other AC adaptors may use a different polarity, or be designed for a different voltage, so their use could result in damage, malfunction, or electric shock.

- Do not excessively twist or bend the power cord, nor place heavy objects on it. Doing so can damage the cord, producing severed elements and short circuits. Damaged cords are fire and shock hazards!






- This unit, either alone or in combination with an amplifier and headphones or speakers, may be capable of producing sound levels that could cause permanent hearing loss. Do not operate for a long period of time at a high volume level, or at a level that is uncomfortable. If you experience any hearing loss or ringing in the ears, you should immediately stop using the unit, and consult an audiologist.





- Do not allow any objects (e.g., flammable material, coins, pins); or liquids of any kind (water, soft drinks, etc.) to penetrate the unit.

WARNING

- Immediately turn the power off, remove the AC adapter from the outlet, and request servicing by your retailer, the nearest Roland Service Center, or an authorized Roland distributor, as listed on the "Information" page when:
 - The AC adaptor, the power-supply cord, or the plug has been damaged; or
 - Objects have fallen into, or liquid has been spilled onto the unit; or
 - The unit has been exposed to rain (or otherwise has become wet); or
 - The unit does not appear to operate normally or exhibits a marked change in performance.
- In households with small children, an adult should provide supervision until the child is capable of following all the rules essential for the safe operation of the unit.
- Protect the unit from strong impact. (Do not drop it!)
- Do not force the unit's adapter to share an outlet with an unreasonable number of other devices. Be especially careful when using extension cords—the total power used by all devices you have connected to the extension cord's outlet must never exceed the power rating (watts/amperes) for the extension cord. Excessive loads can cause the insulation on the cord to heat up and eventually melt through.
- Before using the unit in a foreign country, consult with your retailer, the nearest Roland Service Center, or an authorized Roland distributor, as listed on the "Information" page.

CAUTION

- The unit or the AC adapter should be located so that its location or position does not interfere with its proper ventilation.
- Always grasp only the plug or the body of the AC adaptor when plugging into, or unplugging from, an outlet or this unit.
- Whenever the unit is to remain unused for an extended period of time, disconnect the AC adaptor.
- Try to prevent cords and cables from becoming entangled. Also, all cords and cables should be placed so they are out of the reach of children.
- Never climb on top of, nor place heavy objects on the unit.

- Never handle the AC adapter, or its plugs, with wet hands when plugging into, or unplugging from, an outlet or this unit.
- If you need to move the instrument, take note of the precautions listed below. Make sure to have a firm grip, to protect yourself from injury and the instrument from damage.
 - Check to make sure the knob bolt securing the unit to the stand have not become loose. Fasten them again securely whenever you notice any loosening.
 - Disconnect the adapter.
 - Disconnect all cords coming from external devices.
 - Remove the music stand.
- Before cleaning the unit, turn off the power and unplug the AC adapter from the outlet (p. 8).
- Whenever you suspect the possibility of lightning in your area, disconnect the adapter from the outlet.

IMPORTANT NOTES

In addition to the items listed under “Important Safety Instructions” (inside cover) and “Using the unit safely”, p. 2, please read and observe the following:

Power Supply

- Do not use this unit on the same power circuit with any device that will generate line noise (such as an electric motor or variable lighting system).
- When the AC adaptor is used for extended periods, both the adaptor itself, and the area around the ep-760's DC IN connector will become somewhat warm; however, this does not indicate a malfunction.
- Before connecting the ep-760 to other devices, turn off the power to all units. This will help prevent malfunctions and/or damage to speakers or other devices.
- Be sure to only use the supplied adapter or (in the unlikely event it ceases to function properly) an equivalent Roland ACO adapter.

Placement

- Using the unit near power amplifiers (or other equipment containing large power transformers) may induce hum. To alleviate the problem, change the orientation of this unit; or move it farther away from the source of interference.
- This instrument may interfere with radio and television reception. Do not use this device in the vicinity of such receivers.
- Noise may be produced if wireless communications devices, such as cell phones, are operated in the vicinity of this unit. Such noise could occur when receiving or initiating a call, or while conversing. Should you experience such problems, you should relocate such wireless devices so they are at a greater distance from this unit, or switch them off.
- Do not expose the unit to direct sunlight, place it near devices that radiate heat, leave it inside an enclosed vehicle, or otherwise subject it to temperature extremes. Also, do not allow lighting devices that normally are used while their light source is very close to the unit (such as a piano light), or powerful spotlights to shine upon the same area of the unit for extended periods of time. Excessive heat can deform or discolor the unit.
- To avoid possible breakdown, do not use the ep-760 in a wet area, such as an area exposed to rain or other moisture.
- Do not allow rubber, vinyl, or similar materials to remain on the ep-760 for long periods of time. Such objects can discolor or otherwise harmfully affect the finish.
- Do not put anything that contains water (e.g., flower vases) on the piano. Also, avoid the use of insecticides, perfumes, alcohol, nail polish, spray cans, etc., near the unit. Swiftly wipe away any liquid that spills on the unit using a dry, soft cloth.

- Do not allow objects to remain on the keyboard. This can be the cause of malfunction, such as keys ceasing to produce sound.

Maintenance

- To clean the unit, use a dry, soft cloth; or one that is slightly dampened. Try to wipe the entire surface using an equal amount of strength, moving the cloth along with the grain of the wood. Rubbing too hard in the same area can damage the finish.
- Never use benzine, thinners, alcohol or solvents of any kind, to avoid the possibility of discoloration and/or deformation.

Additional Precautions


- Use a reasonable amount of care when using the ep-760's buttons, sliders, or other controls; and when using its jacks and connectors. Rough handling can lead to malfunctions.
- When connecting/disconnecting cables, grasp the connector itself—never pull on the cable. This way you will avoid causing shorts, or damage to the cable's internal elements.
- A small amount of heat will radiate from the unit during normal operation.
- To avoid disturbing your neighbors, try to keep the unit's volume at reasonable levels. You may prefer to use headphones.
- When you need to transport the unit, pack it in shock-absorbent material. Transporting the unit without doing so can cause it to become scratched or damaged, and could lead to malfunction.
- Use a cable from Roland to make the connection. If using some other make of connection cable, please note the following precautions.
 - Some connection cables contain resistors. Do not use cables that incorporate resistors for connecting to this unit. The use of such cables can cause the sound level to be extremely low, or impossible to hear. For information on cable specifications, contact the manufacturer of the cable.

Contents

Using the unit safely	2
Important Notes.....	4
Panel descriptions	6
Front panel	6
Rear panel.....	7
Before you start playing	8
Connecting the supplied DP-2 footswitch.....	8
Connecting the adapter	8
Setting up the music stand.....	8
Connecting headphones.....	9
Turning the power on/off	9
Adjusting the sound's volume and brilliance.....	9
1. Enjoying the songs	10
Listening to built-in songs	10
Playing back all songs continuously (All Song Play)	10
Selecting a song and playing it	10
2. Performance	11
Performing with a variety of sounds.....	11
Playing two sounds together (Dual performance).....	11
Playing different tones with the left & right hands (Split).....	13
Using the metronome	14
Applying effects to the sound	15
Transposing the keyboard (Transpose)	16
Adjusting the keyboard touch (Key Touch).....	17
3. Playing along with the built-in songs.....	18
Changing the tempo	18
Playing each hand separately.....	19
4. Recording your performance.....	20
Recording a new song	20
Recording along with a song.....	21
Selecting/recording each hand separately	22
Erasing recorded performances	23
5. Changing various settings	24
Changing the damper pedal's resonance	24
Function settings	24
Tuning to other instruments' pitches (Master Tune).....	24
Changing the temperament.....	24
Setting the tuning curve (Stretch Tuning)	25
Applying the damper pedal to the left half.....	25
Disabling everything except piano play (Panel Lock).....	26
6. Connecting external devices	27
Connecting to audio equipment	27
Connecting to a computer.....	27
Connecting MIDI devices.....	28
What's MIDI?.....	28
MIDI transmit channel settings.....	28
Transmitting a performance you recorded	29
Appendices	30
Troubleshooting	30
Error messages/other messages	31
Easy operation list.....	32
Main specifications	33
References	103

Panel descriptions

Front panel



① [Volume] knob

Adjusts the overall volume level (p. 9).

② [Brilliance] button

Adjusts the tone brightness (p. 9).

③ [Transpose] button

Transposes the pitch of the keyboard (p. 16).

④ [Split] button

Divides the keyboard into right-hand and left-hand areas, allowing you to play a different sound in each area (p. 13).

⑤ [Reverb] button

Adds reverberation to the sound (p. 15).

⑥ Tone buttons

They are used to choose the kinds of tones (tone groups) played via the keyboard (p. 11).

⑦ Display

Displays information such as the song number, tempo, beat, and parameter settings values.

⑧ [+/-] buttons

Allow you to select the value of various settings. Pressing both the [+] and [-] buttons simultaneously returns the setting of a particular item or function to its original value.

⑨ [A] Button

Turns the metronome on/off (p. 14). By holding down this button and the [Beat] button, and pressing other specified button, you can make settings for various functions (p. 24, 28).

⑩ [Beat] button

Hold down this button and press the [+] or [-] button to specify the time signature (beat) (p. 14).

⑪ [Song/Tempo] Button

Used to select from the built-in songs (p. 10, 18). Each time you press this button, the song number and the tempo will be displayed alternately.

Recorder

Plays back or records a performance.

⑫ [▶(Play)] button

Starts and stops playback of built-in songs and recorded performances (p. 10, 18).

Also starts/stops recording of a performance (p. 20~p. 22).

⑬ [●(Rec)] button

Puts the ep-760 in recording-standby mode (p. 20~23).

⑭ [1] button

Plays back or records a performance separately for each hand. (p. 19, p. 21~23).

The left-hand performances of the built-in songs are assigned to this button. This button and the following [2] button are collectively referred to as the "track buttons."

⑮ [2] button


Plays back or records a performance separately for each hand (p. 19, p. 21~23).

The right-hand performances of the built-in songs are assigned to this button.

⑯ [Key Touch] button

Modifies the playing feel of the keyboard (p. 17).

Rear panel



① MIDI Out/In connectors

Connect to external MIDI devices to exchange performance data (p. 28).

② Pedal sockets (Damper & Soft)

Your ep-760 comes with one DP-2 footswitch that can be used as Damper, Soft, or Sostenuto pedal (p. 8). In order to use two pedal functions simultaneously, you need to purchase an additional DP-2, DP-6 or BOSS FS-5U footswitch.

③ Input sockets

These jacks can be connected to another sound generating device or an audio device, so that the sound of that device will be output from the ep-760's speakers (p. 27). If your sound source is mono (i.e. only has one output), connect it to the L/Mono socket.

④ Output jacks

Allows you to output the piano's sound to sound reinforcement equipment to obtain a more powerful sound. These can also be connected to a tape recorder or other recording device to record a performance (p. 27). If your amplifier, etc., is mono (i.e. only has one input), connect the ep-760's L/Mono socket.

⑤ [Power] switch

Turns the power on/off (p. 9).


⑥ DC 12V IN

This is where you need to connect the supplied ACO adapter. Do not use any other adapter.

Before you start playing

Connecting the supplied DP-2 footswitch

Connect the supplied pedal to one of the Pedal jacks. A DP-2 is supplied with the ep-760.



If the pedal is connected to the **Damper** jack, it can be used as a damper pedal (to sustain the notes played on the keyboard). If the pedal is connected to the **Soft** jack, it can be used as a soft pedal (to lower the volume).

Damper pedal

While this pedal is pressed, notes will be sustained even after you take your fingers off the keys.

On an acoustic piano, holding down the damper pedal will allow the remaining strings to resonate in sympathy with the sounds that you played from the keyboard, adding a rich resonance. The ep-760 simulates this sympathetic resonance.

MEMO

You can change the amount of resonance applied with the damper pedal. Please refer to "Changing the damper pedal's resonance", p. 24.

Soft pedal

When you hold down this pedal and play the keyboard, the sound will have a softer tone.


Sostenuto pedal

This function allows you to sustain only the sounds of the keys that were already played when you pressed the pedal.

This is a function that needs to be selected (p. 26), in which case the Soft function is no longer available.

Connecting the adapter

- 1 Connect the supplied AC adapter to a wall outlet.
- 2 Connect the ACO adapter to the DC In jack on the rear panel of the ep-760.




NOTE

Strong tension applied to the cord may damage or break it. Be careful not to pull the cord accidentally, or to apply strong pressure to it.

Setting up the music stand

Set up the music stand as shown in the figure below.



NOTE

Before moving the ep-760, be sure to remove the music stand as a safety precaution.


Connecting headphones

The ep-760 has two jacks for plugging in headphones. This allows two people to listen through headphones simultaneously, making it very useful for lessons and when performing piano pieces for four hands. Additionally, this allows you to play without having to worry about bothering others around you, even at night.

Plug the headphones into one of the Phones jacks.

Connecting headphones will automatically mute the sound from the internal speakers.

The headphone volume is adjusted by the [Volume] knob (p. 9) of the ep-760.



NOTE

Be sure to use stereo headphones (such as the Roland RH-25 or RH-50).

Notes on using headphones

- To prevent damage to the cord, handle the headphones only by the headset or the plug.
- Connecting the headphones when the volume of connected equipment is turned up may result in damage to the headphones. Lower the volume on the ep-760 before plugging in the headphones.
- Listening at excessively high volume levels will not only damage the headphones, but may also cause hearing loss. Use the headphones at a moderate volume level.

Turning the power on/off

NOTE

Turn on power to your various devices in the order specified. By turning on devices in the wrong order, you risk causing malfunction and/or damage to speakers and other devices.


To turn the power on, turn the [Volume] knob all the way down, and then press the [Power] switch on the ep-760's rear panel.

After a few seconds, you will be able to play the keyboard to produce sound.

Use the [Volume] knob to adjust the volume.

NOTE


The ep-760 is equipped with a protection circuit. A brief interval (a few seconds) after power up is required before the unit will operate normally.



To turn the power off, turn the [Volume] knob all the way to the left, and press the [Power] switch.

Adjusting the sound's volume and brilliance

Turn the [Volume] knob to adjust the overall volume. Press the [Brilliance] button to adjust the brightness of the sound.



The [Brilliance] button provides access to 3 different timbre settings, which are indicated by the color of its indicator:

Dark: original timbre (as sampled)

Red: rounder/mellower timbre

Green: brighter timbre.

You may have to press it several times in order to select the desired setting.


1. Enjoying the songs

Listening to built-in songs

The ep-760 comes with 65 piano songs on-board. See also "Playing along with the built-in songs", p. 18 and "Songs", p. 106.

■ Playing back all songs continuously (All Song Play)

The built-in songs can be played back consecutively.



- 1 Hold down the [Song/Tempo] button and press the [▶(Play)] button.

The [Song/Tempo] button's indicator will light, the [▶(Play)] button's indicator will flash, and the songs will play back successively, starting with the currently selected song.

The song number appears in the display.


You can press the [+] or [-] button to select the song that you want to play back.

When all songs have been played, playback will return to the first song and resume.

Stopping playback

- 2 Press the [▶(Play)] button.
Playback will stop.

■ Selecting a song and playing it



Choosing the song to play back

- 1 Press the [Song/Tempo] button (its indicator lights red).

The song number appears in the display.



"U5r" (user) refers to the location where you can record your own performances (see also p. 20). Numbers with a "d." refer to built-in songs.

- 2 Press the [+] or [-] button to select a song.
Holding down the button causes the numbers to change continuously.

Starting playback

- 3 Press the [▶(Play)] button.
The button's indicator will light, and the selected song will play.


Stopping playback

- 4 Press the [▶(Play)] button.
The button's indicator goes out, and playback stops. The next time you press the [▶(Play)] button, the song that was stopped is played from the beginning.

2. Performance

Performing with a variety of sounds

The ep-760 contains 20 built-in sounds (or “Tones”). The tones are organized into five Tone groups, which are assigned to the Tone buttons.



Selecting a tone group

① Press any Tone button.

The indicator of the button you pressed will light. When you play the keyboard, you will hear a sound in the selected tone group.

MEMO

For more details, refer to “Tone List”, p. 105.

Selecting Variation tones

② Press the [Variation] button.

Four different tones (numbered 1~4) are assigned to each Tone button. Use the [Variation] button to select among them.

Each time you press the [Variation] button, the button’s indicator will change color, and the four sounds will be selected successively.

Tone number	1	2	3	4
[Variation] indicator	Dark	Red	Green	Orange

Some of the number 3 and 4 tones form pairs, which can be layered and sounded together.

The tone you’ve selected is heard when you finger the keyboard.

MEMO

Dual performance (p. 11) or Split performance (p. 13) can be used when tone numbers 1 or 2 are selected.

If you use Dual performance or Split performance with a Tone button for which tone number 3 or 4 is selected, tone number 1 will be selected for that Tone button.

Playing two sounds together (Dual performance)

Simultaneously playing two tones when one key is pressed is called “Dual performance.” When Dual performance is used, the [Variation] button’s indicator will light to indicate the selection of the right button of the two selected tones.

① Simultaneously press the two Tone buttons that you want to play together.

The indicator of the button you pressed will light. When you play the keyboard, the tones of the two Tone buttons you selected will sound simultaneously. To cancel Dual performance, press any Tone button.

MEMO

Dual performance can be used only with Tones numbered “1” or “2” (see above).

If you use Dual performance with a Tone numbered “3” or “4”, Tone “1” will automatically be selected for that Tone button.

Changing the tone of the right button (modifying the Dual combination)

② Press the [Variation] button.


Dual performance now plays the tone of the left Tone button along with the newly selected tone.

Changing the tone of the left button

Cancel the Dual performance, and then re-select the desired Tones.


■ Adjusting the volume balance in Dual performance (Dual Balance)

You can change the volume balance between the two layered sounds in Dual performance.



- ① Hold down the [Transpose] button, and press the [Split] button.

The indicators of the buttons you pressed will flash. The current volume balance appears in the display.




- ② Press the [+] or [-] button to change the value. To return to the original volume balance, press the [+] and [-] buttons simultaneously. Press any button other than the [+] [-] buttons, and the button's indicator will return to the previous state.

MEMO

When the power is turned on, this will be set to "8-2" (volume of the left button's tone – volume of the right button's tone).

Playing different tones with the left & right hands (Split)

Dividing the keyboard into right-hand and left-hand areas, then playing different sounds in each is called “Split performance.” The boundary key is called the “split point.” The split point key is part of the left-hand keyboard area. Split performance can be used only with Tones numbered “1” or “2” (see the table on page 11). If you use Split performance with a Tone numbered “3” or “4”, Tone “1” will automatically be selected for that Tone button.



① Press the [Split] button.

The button's indicator lights.

The keyboard is divided into right-hand and left-hand areas.

The tone you were playing before you pressed the [Split] button will be selected for the right-hand area, and a tone that is a suitable match for the right-hand tone (e.g., a bass tone) will be selected for the left-hand area.

To cancel Split performance, press the [Split] button, getting its indicator to go dark.

MEMO

When using Dual performance, press the [Split] button.

The right hand will play the tone of the left button of Dual performance, and the left hand will play a suitable match for the right-hand tone.

Changing tone played by the left hand

② Press the [Variation] button.

Each time you press the [Variation] button, the button's indicator will change color, and the left-hand tone will change.

Some tones assign the tone that had been selected before you pressed the [Split] button to the left hand area of the keyboard.

MEMO

- For information about the tones that can be selected for the left hand section, refer to the “Tone List”, p. 105.
- The selected left-hand tone is remembered for each Tone button. When you turn off the power, it will return to the original setting.

Changing tone played by the right hand

③ Press a Tone button.

The tone of the right-hand area will change.

If you want to change the variation for the right-hand tone, cancel Split performance and then re-select the tone.

NOTE

In Split mode, the damper pedal will be applied only to the right-hand area of the keyboard. If you want the damper pedal to be applied to the left-hand area, refer to “Applying the damper pedal to the left half”, p. 25.

Changing the keyboard's split point

You can change the location where the keyboard is divided (the split point) within the range of B2~B6. The setting is at "F#3" when the piano is powered up.



- ④ While continuing to hold the [Split] button, press the key that you want to specify as the split point.

The key you press becomes the split point, and belongs to the left-hand section of the keyboard.

You can also change the setting by pressing the [+] or [-] button while continuing to hold down the [Split] button.

The split point key is displayed as follows.

Display	C	d _♭	d	E _♭
Letter name	C	D _♭	D	E _♭
Display	E	F	F _♯	G
Letter name	E	F	F _♯	G
Display	A _♭	A	b _♭	b
Letter name	A _♭	A	B _♭	B

If you hold down the [Split] button and simultaneously press the [+] and [-] buttons, the setting will return to its original value (F#3).


MEMO

When you continue holding the [Split] button, the currently specified split point value will be displayed.

Using the metronome

■ Sounding the metronome

The ep-760 features a built-in metronome. While a song plays back, the metronome will sound at the tempo and time signature (Beat) of that song.



Sounding the metronome

- ① Press the [M] button.

The metronome will sound. The button's indicator flashes red and green in time with the beat selected at that time. The indicator lights in red on the downbeats, and in green on weak beats.

Changing the tempo

- ② Press the [+] or [-] button to adjust the tempo.

Changing the beat of metronome

- ③ Press the [Beat] button, followed by the [+] or [-] button.

The currently selected time signature will be displayed. If you press the [Beat] button and [+] or [-], the beat will change.


If you press the [+] and [-] buttons simultaneously, the beat will return to what it was before you changed it.



Beat	Tempo Value
2/2	♩=10-125
x/4	♩=20-250
x/8	♩=40-500

Display	Beat	Display	Beat
2.2	2/2	6.4	6/4
0.4	Only weak beats	7.4	7/4
2.4	2/4	3.8	3/8
3.4	3/4	6.8	6/8
4.4	4/4	9.8	9/8
5.4	5/4	12.8	12/8

Stopping the metronome

- Once again press the [] button, getting its indicator to go dark.

The metronome will stop.

NOTE


It is not possible to change the beat during song playback or recording.


Selecting another metronome sound

- While holding down the [Beat] button, use the [+] or [-] button to select another sound.


Changing the metronome volume

The volume of the metronome can be adjusted, with eight volume levels available. It is set to “4” when the instrument is turned on.

- While holding down the [] button, press the [+] or [-] button.

The currently specified volume will be displayed. Continue to hold down the [] button, and press the [+] or [-] button to sound the metronome and change the volume.

Applying effects to the sound



Adding reverberation to the sound (Reverb)

By applying the reverb effect you can produce a pleasant reverberation, making it sound as though you were performing in a concert hall.

- Press the [Reverb] button.
The button's indicator will light, and a reverb effect will be applied to the sound.
- To cancel the reverb effect, press the [Reverb] button, getting its indicator to go dark.

NOTE

- The Reverb effect setting for the Tones is not remembered.
- When you play back a built-in song, the reverb effect will automatically be turned on (the button's indicator lights).

Chorus effect

The ep-760 also features a Chorus effect that is automatically switched on whenever you select an “E.Piano” Tone. The level cannot be changed, nor is the effect available for other Tones.

MEMO

When using Split performance (p. 13), the Chorus effect will not be applied to the left-hand bass tone of the keyboard (p. 105).

Changing the amount of Reverb

The depth of the Reverb effect can be adjusted over eight steps.

MEMO

When the power is turned on, Reverb is set to “4”.

- Hold down the [Reverb] button and press the [+] or [-] button.
The currently specified value will be displayed. Higher values will produce a deeper effect.


MEMO

- The depth of the Reverb effect for the Tones is not remembered.

Transposing the keyboard (Transpose)

By using the “Transpose function,” you can transpose your performance without changing the notes you play. For example, even if the song is in a difficult key with numerous sharps (\sharp) or flats (\flat), you can transpose it to a key that is easier for you to play.

When accompanying a vocalist, you can easily transpose the pitch to a range that is comfortable for the singer, while still playing the notes as written (i.e., with the same fingering positions).



- ① **Hold down the [Transpose] button, and press a note to indicate the tonic of the key to which you want to transpose.**

The button's indicator will light, and the keyboard will be transposed.

MEMO


When you hold down the [Transpose] button, the currently specified value will be displayed.

You can change the transposition interval by holding down [Transpose] and pressing the [+] or [-] button. If you hold down the [Transpose] button and press the [+] and [-] buttons simultaneously, the setting will return to the original value (0).

This can be set in a range of -6~0~5 (semitone steps).

For example, if you want the E pitch to sound when you play the C key, hold down the [Transpose] button and press the E key.

Counting from C as a reference point, one moves up four keys, including the black keys, to reach E, thus “4” appears in the display.



When the transpose value is set to “0”, the button's indicator will remain dark even if you press the [Transpose] button.

To cancel the transpose function, press the [Transpose] button, extinguishing its indicator.


When you press the [Transpose] button once again, getting its indicator to light, the keyboard will be transposed to the note you specified here.

MEMO

This setting returns to the original value (0) when you turn off the power.

Adjusting the keyboard touch (Key Touch)

You can adjust the touch (playing feel) of the keyboard.



① **Press the [Key Touch] button.**

The button's indicator will light, and the feel of the keyboard will change.

Each time you press the [Key Touch] button, the button's indicator will change color, and the feel of the keyboard will change.

Indicator	Settings	
OFF	Medium	This allows you to play using the most natural touch. This is the closest to the touch of an acoustic piano.
Red	Heavy	Fortissimo (ff) cannot be produced unless you play more strongly than usual, making the keyboard feel heavier. Dynamic fingering adds even more feeling to what you play.
Green	Light	Fortissimo (ff) can be produced by playing less strongly than usual, making the keyboard feel lighter. This setting makes it easy to play, even for children.
Orange	Fixed	Sounds at a fixed volume, regardless of your keyboard playing strength.

3. Playing along with the built-in songs

Here's how you can play along with the built-in songs. You can slow down the playback tempo of the song, or play back each hand separately.


Before you try playing the song, listen to it several times to get a general feel for the song. For details on operation, refer to "Selecting a song and playing it", p. 10.



If you turn on the metronome while the song plays back, the metronome will sound at the beat and tempo of the song.

Changing the tempo

If the song has a rapid tempo, you can slow it down so as to practise it more easily. It is effective to gradually raise the tempo as you practise.



- ① Press the [Song/Tempo] button, getting its indicator to light in green.

The tempo appears in the display.

Each time you press the [Song/Tempo] button, the tempo and the currently selected song number (prefixed by "d.") will be displayed alternately.

While the tempo is displayed, the [Song/Tempo] button indicator will light in green. While the song number is displayed, it will light in red.

- ② Press the [+] or [-] button to adjust the tempo.

The tempo can be adjusted in a range of $\text{♩} = 20\sim 250$. You can also change the tempo during playback.

Pressing the [+] button once increases the tempo by one unit. Holding down the button increases the tempo continuously.

Pressing the [-] button once decreases the tempo by one unit. Holding down the button makes the tempo change (slow down) continuously.

If you press the [+] and [-] buttons simultaneously, you will return to the basic tempo of the song (the tempo before you modified it).



While the song is playing, the initial tempo of the song will continue to be displayed, regardless of tempo changes during the song.

Adding a count-in to match the timing (Count-In)

When you're playing along with a song, you can make sure that your playing is in time with the song by sounding a count before the song starts playing. Sounding a "count sound" leading up to playback of a song is called "Count-In."

On the ep-760, if you playback a song while the metronome is sounding, two measures of lead-in count will be heard at the beginning of the song.




- During the count-in, the count measure is indicated in the display as "-2" then "-1."
- See also "Sounding the metronome", p. 14.

Playing each hand separately

The built-in songs allow you to select the performance part that will be played back.

The left-hand performance of the built-in songs is assigned to the [1] button, while the right-hand performance is assigned to the [2] button. The place where each part of the performance is held is called a “track,” and the [1] and [2] buttons are called “track buttons.”


Here’s how to practice each hand separately along with the song.



- ① First select the song that you want to play back (p. 10).

Selecting the part that you yourself will play

- ② Press the [1] or [2] button.
The indicator of the button you’ve pressed goes out, and the sound of the selected part will no longer be heard.



For example, if you want to practice the right hand, press button [2] and get its indicator to go dark. When you play back the song, the right-hand performance will not sound. Practise your right-hand performance along with the left-hand playback.

Starting playback

- ③ Press the [▶(Play)] button.
The song will begin playing back.
The part you selected in step ② will not sound.
Once again press the button you selected in step ②.
The button’s indicator will light, and the sound will be heard once again.
Even while the song is playing, you can press the track buttons to mute or un-mute the sound.


Stopping playback

- ④ Press the [▶(Play)] button.
The song will stop.

Selecting/recording each hand separately

The recorder of the ep-760 has two recording tracks, allowing you to record the left and right hands separately. Use the [1] or [2] button to specify the recording track.

If you want to re-do the recording, you can re-record just a specific track.



As described in steps ① and ② of “Recording a new song”, p. 20, select the song “U5r” before you continue.

NOTE

If you record additional material without erasing the recorded song, the song tempo, beat, and metronome settings of the original recording will be used for the new material as well.

- ① As necessary, turn on the metronome (p. 14).
- ② Press the [●(Rec)] button.
The [●(Rec)] button’s indicator will light.
The button indicators of tracks that are already recorded will light.
The track button to which you will be recording will flash.

Selecting the track to record

- ③ Press the [1] or [2] button to select the track that you want to record.
The indicator of the button you pressed will flash, and the ep-760 enters recording-standby mode.

MEMO

The track buttons allow you to record to either the [1] or the [2] button, one at a time.

Start recording

- ④ Press the [▶(Play)] button.
Go ahead and perform on the keyboard.
Note that recording will also begin as soon as you play on the keyboard, even if you do not press the [▶(Play)] button. There is no count sound played when you start in this manner.

Stop recording

- ⑤ Press the [▶(Play)] or [●(Rec)] button.
Recording will stop, and the indicators for the [▶(Play)] and [●(Rec)] buttons will go dark.
Your performance has been recorded to the specified track button.
If you want to record on the other track, return to step ② to record your performance again. You can record while you listen to the previously recorded performance.

Play back the recorded performance

- ⑥ Press the [▶(Play)] button.
You will hear the recorded performance.
Press the [▶(Play)] button once again, and playback will stop.

Erasing recorded performances

You can erase a recorded performance.

Erasing a performance from the specified track

You can select a recorded track and erase it.

- ① **Hold down either the [1] or [2] button, and press the [●(Rec)] button.**

The indicator of the button you pressed will go dark, and the performance of the selected track will be erased.

Erasing the entire song

You can erase a song you've recorded.

- ① **Hold down the [Song/Tempo] button and press the [●(Rec)] button.**

The following display will appear, and the [●(Rec)] button's indicator will flash.



- ② **Once again press the [●(Rec)] button.**

The recorded performance is erased.

If you decide not to erase the performance, press the [▶(Play)] or [Song/Tempo] button.

5. Changing various settings

Changing the damper pedal's resonance

On an acoustic piano, the damper pedal causes the notes you play to resonate along with other strings, adding rich reverberations and fatness to the sound. The damper function on the ep-760 recreates this resonance (Sympathetic Resonance) when depressed.

You can select from eight levels of depth for the resonant sound (resonance level).

This is set to "5" when the instrument is turned on.

NOTE

- This setting is valid only for some piano tones. It cannot be made for other Tones.
 - This function is only meaningful if you connect the supplied DP-2 footswitch to the Pedal [Damper] socket.
- ① Hold down the [Reverb] and [Split] buttons, and press the [-] or [+] button.

The currently specified value will be displayed. Larger values produce a deeper effect.



For details on each function, refer to the explanations below.

- ③ Press the [+] or [-] button to change the value.
Press the [+] and [-] buttons simultaneously to return to the initial setting.

Leaving Function mode

- ④ Press the [Metronome] or [Beat] button.
The button's indicator will return to the previous state.

Tuning to other instruments' pitches (Master Tune)

When playing ensemble with other instruments, you can tune the ep-760's reference pitch to the pitch of another instrument. The standard pitch generally refers to the pitch of the note that's played when you finger the middle A key. This tuning of all the instruments to a standard pitch is called "tuning."

If you press the [Piano] button in step ② of "Function settings", a display like the following will appear.



The last three digits are indicated in the display. "440.0 Hz" is indicated in the figure above.

Setting range: 415.3 Hz~440.0Hz~466.2 Hz

Initial setting: 440.0 Hz

This setting remains in effect until you turn off the power.

Function settings

You can make performance-related settings such as tuning and temperament.

How to enter function mode

- ① Hold down the [Metronome] button, and press the [Beat] button.

The indicators of the buttons you pressed will flash, and you will enter Function mode. The display now indicates the value of the currently selected function.

Setting the various functions

- ② Press the button to which the desired function is assigned.

The indicator of the button you pressed flashes.

Button	Function	Page
[Piano]	Master Tuning	p. 24
[E. Piano]	Temperament	p. 24
[Harpichord]	Stretch Tuning	p. 25
[Organ]	Applying the damper pedal also to the left-hand keyboard area	p. 25
[Strings]	MIDI transmit channel	p. 28
[Variation]	Local Control	p. 29
[▶(Play)]	Transmitting a recorded performance	p. 29
[●(Rec)]	Selecting the Soft/Sostenuto function	p. 26

Changing the temperament

You can play classical styles such as Baroque using historic temperaments (tuning methods).

Nowadays, compositions are generally created with equal temperament in mind and are played using equal temperament. However, in the past, a variety of temperaments were used. Playing a composition with its original tuning lets you enjoy the sonorities of the chords that the composer originally intended.

If you press the [E.Piano] button in step ② of "Function settings", a display like the following will appear.



Temperament Tonic

You can choose from among the seven temperaments described below.

Display	Temperament	Qualities
1	Equal	In this tuning, each octave is divided into twelve equal steps. Every interval produces about the same amount of slight dissonance. This setting is in effect when you turn on the power.
2	Pythagorean	This tuning, devised by the philosopher Pythagoras, eliminates dissonance in fourths and fifths. Dissonance is produced by third-interval chords, but melodies are euphonious.
3	Just Major	This tuning eliminates ambiguities in the fifths and thirds. It is unsuited to playing melodies and cannot be transposed, but is capable of beautiful sonorities.
4	Just Minor	The Just tunings differ from major and minor keys. You can get the same effect with the minor scale as with the major scale.
5	Mean Tone	This scale makes some compromises in just intonation, enabling transposition to other keys.
6	Werckmeister	This temperament combines the Mean Tone and Pythagorean tunings. Performances are possible in all keys (first technique, III).
7	Kirnberger	This is an improvement of the Mean Tone and Just tunings that provides a high degree of freedom of modulation. Performances are possible in all keys (III).

Initial setting: C

Tonic

When playing with tuning other than equal temperament, you need to specify the keynote for tuning the song to be performed (that is, the note that corresponds to C for a major key or to A for a minor key).

While holding down the [E. Piano] button, and press a note to specify the desired tonic key.

The tonic note you specify will be displayed as follows.

Display	C	d_	d	E_	E	F	F	G	A_	A	b_	b
Letter name	C	D \flat	D	E \flat	E	F	F \sharp	G	A \flat	A	B \flat	B

If you choose an equal temperament, there's no need to select a keynote.

NOTE

- If you record with a temperament other than equal temperament selected, and then want to play back that performance, use this setting to select the same temperament for playback as the temperament you used when recording.
- When performing in ensemble with other instruments, be aware that depending on the key, there may be some shifting of the pitch. Tune the ep-760 to the fundamental pitch of the other instruments.

Setting the tuning curve (Stretch Tuning)

An acoustic piano is generally tuned to a pitch with a lower bass range and a higher treble range than equal temperament. This special tuning method for pianos is called "Stretch Tuning."

If you press the [Harpichord] button in step ② of "Function settings", p. 24, a display like the following will appear.



Setting range:

- OFF This is the standard tuning curve. This is the right choice when using Dual performance (p. 11), or when playing in ensemble with other instruments.
- On This tuning curve expands the bass and treble ends somewhat. It is suitable for performances such as piano solos. This setting is in effect when you turn on the power.

Initial setting: On

NOTE

This effect works only with the piano tones.

Applying the damper pedal to the left half

When you are using Split performance (p. 13), you can apply the damper pedal effect to the sound played by the left-hand keyboard range.

If you press the [Organ] button in step ② of "Function settings", p. 24, a display like the following will appear.



NOTE

This function is only meaningful if you connect the supplied DP-2 footswitch to the Pedal [Damper] socket.

Setting range:

- OFF The damper pedal effect will not be applied to the sound of the left-hand keyboard area.
- On The damper pedal effect will be applied to the sound of the left and right hand keyboard area.

Initial setting: OFF

Selecting the Soft or Sostenuto function

A footswitch (such as the supplied, or an optional DP-2, DP-6 or BOSS FS-5U) connected to the Pedal [Soft] socket can also be used as Sostenuto pedal.

If you press the **[●(Rec)]** button in step ② of “Function settings”, a display like the following will appear.



Setting range: SFT (Soft), STr (Sostenuto)

Initial setting: SFT

Press [+] to select STr and [-] to select SFT.

SFT: When you hold down this pedal and play the keyboard, the sound will have a softer tone.

STr: This function allows you to sustain only the sounds of the keys that were already played when you pressed the pedal.

Disabling everything except piano play (Panel Lock)

The “Panel Lock” function locks the ep-760 in a state where only piano performance can be used, and all buttons will be disabled. This prevents the settings from being inadvertently modified even if children press the buttons accidentally.

In the Panel Lock state, only the grand piano sound can be played.

- ① Turn the volume to the minimum, and press the [Power] switch to turn off the power.
- ② Hold down the [Piano] button, and press the [Power] switch to turn on the power.

Then, continue to hold down these two buttons for a few seconds.

The following display will appear.



All buttons are disabled. When you play the keyboard, the grand piano sound will be heard.

You can adjust the volume, though.

To defeat the Panel Lock function, turn the volume down to the minimum, and turn on the power once again.

6. Connecting external devices

Connecting to audio equipment

You can connect audio devices to play the sound of the ep-760 through the speakers of your audio system, or to record your performance on a tape recorder or other recording device.


When connecting, please use an audio cable with a standard phone plug (sold separately).

Connection examples

NOTE

To prevent malfunction and/or damage to speakers or other devices, always turn down the volume, and turn off the power on all devices before making any connections.

Playing the sound of the ep-760 through the speakers of an audio system/Recording the performance of the ep-760 on a recording device




Use the following procedure when turning on the power:

- 1 Turn on the power of the ep-760.
- 2 Turn on the power of the connected device.
- 3 Adjust the volume of each device.

When recording ep-760 performances with a cassette deck, etc.

- 4 Start recording on the connected device.
- 5 Perform on the ep-760.
- 6 When the performance ends, stop recording on the connected equipment.

Playing the sound of an audio device through the speakers of the ep-760



Use the following procedure when turning on the power.

- 1 Turn on the power of the connected device.
- 2 Turn on the power of the ep-760.
- 3 Adjust the volume of each device.

Turning off the power

- 1 Set the volume of the ep-760 and of the connected devices to the minimum position.
- 2 Turn off the power to the ep-760.
- 3 Turn off the connected equipment.

Connecting to a computer

You can use a USB MIDI interface cable (sold separately) to connect the ep-760 to your computer.


If the ep-760 is connected to a computer running sequencer software such as Roland's "Visual MT", a song you've recorded on the ep-760 can be saved on your computer.

Connection examples

NOTE

- To prevent malfunction and/or damage to speakers or other devices, always turn down the volume, and turn off the power on all devices before making any connections.
- In order to make connections to your computer, you must install MIDI driver software on your computer. For details, refer to the owner's manual for your MIDI interface.

Use a USB MIDI interface cable to connect the USB connector of your computer to the MIDI connectors of the ep-760.



Connecting MIDI devices

By connecting an external MIDI device and exchanging performance data, you can control the performances on one device from the other. For instance, you can output sound from the other instrument or switch Tones on the other instrument.

What's MIDI?

MIDI stands for "Musical Instrument Digital Interface", an international standard which allows performance information to be communicated among electronic musical instruments and computers.


The ep-760 provides MIDI connectors, which allow performance data to be exchanged with external devices. When these connectors are used to connect the ep-760 to external devices, an even wider range of possibilities becomes available.

Connection examples

NOTE


To prevent malfunction and/or damage to speakers or other devices, always turn down the volume, and turn off the power on all devices before making any connections.

Playing the ep-760 from a MIDI sequencer/ Recording an ep-760 performance on a MIDI sequencer



Set Local Off if you have connected the ep-760 to a MIDI sequencer. Refer to "Switching Local Control on and off", p. 29. Also set your MIDI sequencer to MIDI Thru mode (so that messages received at MIDI IN will be re-transmitted without change from MIDI OUT). For details, refer to the owner's manual of your MIDI sequencer.

Perform on the ep-760 to play a MIDI sound generator



Making MIDI-related settings

Here's how you can set the transmit channel and other MIDI-related settings.

How to enter function mode

- 1 Hold down the [Metronome] button, and press the [Beat] button.

The indicators of the buttons you pressed will flash, and you will enter Function mode. The display now indicates the value of the currently selected function.

Setting various functions

- 2 Press the button to which the desired function is assigned.
The indicator of the button you pressed flashes. For details on each function, refer to the explanations below.
- 3 Press the [+] or [-] button to change the value.
Press the [+] and [-] buttons simultaneously to return to the initial setting.

Leaving Function mode

- 4 Press the [Metronome] or [Beat] button.
The button's indicator will return to the previous state.

MIDI transmit channel settings

MIDI features sixteen MIDI channels, numbered 1~16. Simply connecting a cable is not enough for communication to take place. The connected devices must be set to use the same MIDI channels. Otherwise, no sound will be produced, and no sounds can be selected.

NOTE

- The ep-760 receives all channels 1~16.
- If you are using Dual performance (p. 11) or Split performance (p. 13) on the ep-760, only the channel you specify here will be transmitted.

If you press the [Strings] button in step ② of "Making MIDI-related settings", a display like the following will appear.




Setting range: 1~16
Initial setting: 1


Switching Local Control on and off

When connecting a MIDI sequencer, set Local Control to "Off".


As illustrated, information describing what has been played on the keyboard is passed to the internal sound generator over two different routes, (1) and (2). As a result, you hear overlapping or intermittent sounds. To prevent this from happening, route (1) must be severed, by setting the unit to what is known as "Local Off."



Local Control **On**: The keyboard and the internal sound generator are in a linked state.



Local Control **Off**: The keyboard and the internal sound generator are in an unlinked state. No sound will be produced by the keyboard when it is played.



NOTE

When a Roland MT series instrument is connected, it is not necessary to make the Local Off setting. MT units transmit Local Off messages when their power is switched on. If you turn on the power in the order of the ep-760 → MT series, Local Off will be set automatically.

If you press the [Variation] button in step ② of "Making MIDI-related settings", p. 28, a display like the following will appear.



Setting range: On, OFF
Initial setting: On

Transmitting a performance you recorded

If you want to transmit a performance recorded on the ep-760 to an external MIDI device or computer, turn this setting **Off**. If this is **OFF**, the data will not be transmitted. If you press the [▶(Play)] button in step ② of "Making MIDI-related settings", a display like the following will appear.



Setting range: On, OFF

Initial setting: OFF

To save the performance, use the following procedure. In this situation, your external sequencer is set its MIDI Thru feature to be OFF. For details, refer to the owner's manual of your MIDI sequencer.

- ① Connect a MIDI sequencer such as the MT series (p. 28).
- ② Record the performance on the ep-760 (p. 20).
- ③ Set this setting to "On."
- ④ Start recording with the connected MIDI device.
- ⑤ Start playback of the recorded song on the ep-760.

When playback ends, stop recording on the connected MIDI device.

Use a connected MIDI sequencer to save the data on a floppy disk or other media.

Appendices

Troubleshooting

If you think there's a problem, read this first.

The power doesn't come on

- Is the adapter connected and plugged in correctly? (p. 8)

The buttons do not work

- Is the panel locked (p. 26)? Turn the power off, then back on.

No sound is heard

- Is the volume of the ep-760 turned all the way down? (p. 9)
- Are headphones plugged in? (p. 9)
- Has a plug remained connected to one of the Phones jacks? When headphones are connected, the speakers stop playing.
- Is Local Off selected? When Local Control is set to OFF, no sound is produced by playing the keyboard. Set Local Control to "On" (p. 29)

No sound is heard (when a MIDI instrument is connected)

- Have all devices been switched on?
- Are the MIDI cables connected correctly?
- Does the MIDI channel match the connected instrument? (p. 28)

Sounds are heard twice (doubled) when the keyboard is played

- Is the ep-760 in Dual mode? (p. 11)
- When the ep-760 is connected to an external sequencer, set it to the Local OFF mode (p. 29).
Alternatively, the sequencer could be set so its MIDI Thru feature is OFF.

The tone has changed in Split or Dual mode.

- If you use Dual or Split mode with a Tone button for which tone number "3" or "4" is selected, tone number "1" will be selected for that Tone button (p. 11).
- Some tones assign the tone that had been selected before you pressed the [Split] button to the left hand area of the keyboard. Please refer to "Tone List", p. 105.

Tone doesn't change

- Is the panel locked? (p. 26)
Turn the power off, then back on.
- Are the indicators for the [Metronome] and [Beat] buttons flashing? The Function mode is selected. Press the [Metronome] or [Beat] button to exit function mode (p. 24, p. 28).

Not all notes you play are sounded

- The maximum number of notes that the ep-760 can play simultaneously is 64.
Frequent use of the damper function when playing along with a song may result in performance data with too many notes, causing some notes to drop out.

The tuning or pitch of the keyboard or song is off

- Have you set Transpose? (p. 16)
- Are the settings for the "Temperament" and "Stretch Tuning" correct? (p. 24)
- Is the setting for the "Master Tuning" correct? (p. 24)

Song doesn't play back/Only the sound of a particular instrument in a song does not play

- Are the indicator for the Track buttons ([1] and [2] buttons) extinguished? (p. 19)
If the button indicator is off, the music on that track is not heard. Press the track button so the indicator is illuminated.

Can't record

- Has one of the track buttons for recording been selected? (p. 22)

Tempo of recorded song or metronome is off

- If you select an internal song in which the tempo changes during the song, and then record, the tempo will change in the same way for the performances. The tempo of the metronome will also change in the same way.
- If you record additional material without erasing the previously recorded song, the song will be recorded at the first-recorded tempo. Please erase the previously recorded song before you re-record. (p. 23)

The recorded performance has disappeared

- Any performance that has been recorded is deleted when the power to the ep-760 is turned off. A performance cannot be restored once it's been deleted.

Reverberation still audible even with Reverb turned off

- Since the ep-760's piano sounds faithfully reproduce the sense of spaciousness and reverberation of an actual acoustic piano's sound, a certain amount of reverberation is still perceptible, even with the Reverb effect deactivated. This only applies if you connect the supplied DP-2 footswitch to the Pedal [Damper] socket.

In the upper range, the sound changes abruptly beyond a certain key

- On an acoustic piano, notes in the upper one and a half octaves of the keyboard continue to sound until they decay naturally, regardless of the damper pedal. There is a difference in the timbre as well. Roland pianos faithfully simulate such characteristics of the acoustic piano. On the ep-760, the range that is unaffected by the damper pedal will change depending on the Key Transpose setting.

A high-pitched whine is produced

- When listening through headphones:
Some of the more flamboyant and effervescent piano tones feature an ample high-end component, which may make the sound appear to have metallic reverberation added. Since this reverberation becomes particularly audible when supplemented by heavy reverb, you may be able to diminish the problem by reducing the amount of reverb applied to the sound.
- When listening through speakers:
Here, a different cause (such as resonance produced by the ep-760) would be suspect. Consult your Roland dealer or nearest Roland Service Center.

The bass range sounds odd, or there is a vibrating resonance

- When listening through speakers:
Playing at loud volumes may cause instruments near the ep-760 to resonate. Resonance can also occur with fluorescent light tubes, glass doors, and other objects. In particular, this problem occurs more easily when the bass component is increased, and when the sound is played at higher volumes. Use the following measures to suppress such resonance:
 - Place speakers so they are 10–15 cm from walls and other surfaces.
 - Reduce the volume.
 - Move the speakers away from any resonating objects.
- When listening through headphones:
Here, a different cause (such as resonance produced by the ep-760) would be suspect. Consult your Roland dealer or nearest Roland Service Center.

The volume level of the instrument connected to Input jacks is too low

- Are you using a connection cable that contains a resistor?
Use a connection cable that does not contain a resistor.

Error messages/other messages

Display	Meaning
USr	User. Stores recorded performances (p. 20).
USr.	The "." in the display indicates that there is performance material already recorded (p. 20).
d.	Built-in song number (p. 10).
PU	This appears when a song with a pickup (a song that does not start on the first beat) is played back.
dEL	This appears when you attempt to delete a recorded song (p. 20, p. 23).
E 32	The amount of performance information is too large, and further recording is not possible.
E 41	A problem such as a loose MIDI cable occurred. Make sure the MIDI cables are correctly hooked up.

- * Error messages are indicated by an "E." before the number. Press any button to cancel the error message.

Easy operation list

Here's a quick run-down of all functions provided by your ep-760, and how to access them.

"+" means "press while holding down the preceding button".

"→" means "release the previous button(s) and press".

Master Tuning (p. 24)

- [Metronome] + [Beat] → [Piano]

Temperament/Specifying the keynote (p. 24)

- [Metronome] + [Beat] → [E. Piano]
→ [E. Piano] + key

Stretch tuning (p. 25)

- [Metronome] + [Beat] → [Harpichord]

Damper pedal for the left-hand keyboard area (p. 25)

- [Metronome] + [Beat] → [Organ]

MIDI transmit channel (p. 28)

- [Metronome] + [Beat] → [Strings]

Local Control (p. 29)

- [Metronome] + [Beat] → [Variation]

Transmitting a recorded performance (p. 29)

- [Metronome] + [Beat] → [▶ (Play)]


Selecting the Soft or Sostenuto function for the footswitch connected to [Soft] (p. 26)

- [Metronome] + [Beat] → [●(Rec)]

Metronome beat (time signature) (p. 14)

- [Beat] + [-] [+]

Metronome volume (p. 15)

- [] + [-] [+]

Reverb depth (p. 15)

- [Reverb] + [-] [+]

Damper pedal's resonance level (p. 24)

- [Reverb] + [Split] + [-] [+]

Dual balance (p. 12)

- [Transpose] + [Split] → [-][+]

Split point (p. 14)

- [Split] + key

Key Transpose (p. 16)

- [Transpose] + key
-

Main specifications

Keyboard	
Keyboard	76 keys
Touch Sensitivity	Preset 4 Levels
Keyboard mode	Whole, Dual (adjustable dual balance), Split (adjustable split point)
Sound Generator	
Max. polyphony	64 voices
Tones	5 groups, 20 variations
Temperament	7 types, selectable tonic
Stretched Tuning	2 types
Master tuning	415.3 Hz~466.2 Hz (0.1 Hz Step)
Transpose	Key Transpose (-6~+5 half-steps)
Effects	Reverb (8 levels), Chorus (E. Piano), Sympathetic Resonance (for Piano only, 8 levels)
Metronome	
Beat	2/2, 0/4, 2/4, 3/4, 4/4, 5/4, 6/4, 7/4, 3/8, 6/8, 9/8, 12/8
Volume	8 levels
Recorder	
Tracks	2 tracks
Song	1 song
Note Storage	±5,000 notes
Tempo	Quarter note = 20~250
Resolution	96 ticks per quarter note
Control	Play/Stop, Rec, Tempo, All Song Play, Track Select
Preset Songs	65 songs
Others	
Rated Power Output	5W x 2
Speakers	12 cm x 2
Display	7-segment, 3-digit LED
Control	Volume, Brilliance (button)
Pedal connectors	Damper, Soft (or Sostenuato)
Other Functions	Panel lock
Connectors	Output jacks (L/Mono, R), Input jacks (L/Mono, R), Headphone jacks x 2 (Stereo), MIDI In/MIDI Out connectors
Power supply	ACO adapter, 12V/1A (supplied)
Dimensions	1167.8 (W) x 380.5 (D) x 101.5 (H) mm
Weight	10.5 kg
Accessories	Owner's manual, ACO adapter, DP-2 footswitch
Options	DP-2, DP-6, FS-5U footswitch, KS-EP760 stand, RH-25 or RH-50 headphones

* In the interest of product improvement, the specifications and/or appearance of this unit are subject to change without prior notice.

Reference

Tone List

Button name	[Variation]	[Split] Off	[Split] On		
		Tone	[Variation] Dark	[Variation] Red	[Variation] Green
[Piano]	Dark	Grand Piano1	Grand Piano1 /Acoustic Bass *	Grand Piano1 /Acoustic Bass & Cymbal *	Grand Piano1 /Strings
	Red	Grand Piano2	Grand Piano2 /Acoustic Bass *	Grand Piano2 /Acoustic Bass & Cymbal *	Grand Piano2 /Strings
	Green	Piano + Strings			
	Orange	Piano + Choir			
[E. Piano]	Dark	Electric Piano1	Electric Piano1// Electric Bass *	Electric Piano1 /Acoustic Bass *	Electric Piano1 /Strings
	Red	Electric Piano2	Electric Piano2 /Electric Bass *	Electric Piano2 /Acoustic Bass *	Electric Piano2 /Strings
	Green	Vibraphone			
	Orange	Electric Piano+Choir			
[Harp- sichord]	Dark	Harpichord	Harpichord /Strings	Harpichord /Organ Flute	Harpichord /Acoustic Bass *
	Red	Organ Flute	Organ Flute /Organ Bass	Organ Flute /Strings	Organ Flute /Choir
	Green	Harpichord + Strings			
	Orange	Harpichord + Choir			
[Organ]	Dark	Church Organ	Church Organ /Organ Bass	Church Organ /Strings	Church Organ /Choir
	Red	Rotary Organ	Rotary Organ /Lower Organ	Rotary Organ /Electric Bass *	Jazz Organ /Rotary Organ
	Green	Organ + Strings			
	Orange	Organ + Choir			
[Strings]	Dark	Strings	Strings /Pizzicato	Strings /Choir	Oboe /Strings
	Red	Slow Strings	Slow Strings /Pizzicato	Slow Strings /Choir	Flute /Slow Strings
	Green	Strings + Choir			
	Orange	Strings + Brass			

- * A+B: simultaneously playing two tones
- A/B: A, the right-hand tone; and B, the left-hand tone in Split performance
- * * indicates a tone that will not be applied the Chorus effect.

Songs

Song No.	Song Name	Composer	Copyright
d. 1	Iére Arabesque	C. Debussy	© 1995 Roland Corporation
d. 2	Late Night Chopin	F. Chopin/ Arranged by John Maul	© 2002 Roland Corporation
d. 3	Sonate für Klavier No. 15	W. A. Mozart	© 1996 Roland Corporation
d. 4	Fly Free	J. Maul	© 1998 Roland Corporation
d. 5	Liebesträume III	F. Liszt	© 2001 Roland Corporation
d. 6	Étude, op.10-3	F. Chopin	© 2001 Roland Corporation
d. 7	Je te veux	E. Satie	© 1997 Roland Corporation
d. 8	Valse, op.64-1	F. Chopin	© 2001 Roland Corporation
d. 9	Golliwog's Cake walk	C. Debussy	© 1995 Roland Corporation
d. 10	Fantaisie-Impromptu	F. Chopin	© 2001 Roland Corporation
d. 11	An der schönen, blauen Donau	J. Strauss	© 1996 Roland Corporation
d. 12	Auf Flügeln des Gesanges	F. Mendelsshon	© 1996 Roland Corporation
d. 13	Mazurka No.5	F. Chopin	© 1995 Roland Corporation
d. 14	Ière Gymnopédie	E. Satie	© 1997 Roland Corporation
d. 15	Étude, op.25-1	F. Chopin	© 1995 Roland Corporation
d. 16	Clair de Lune	C. Debussy	© 1998 Roland Corporation
d. 17	Étude, op.10-5	F. Chopin	© 2001 Roland Corporation
d. 18	Doctor Gradus ad Parnassum	C. Debussy	© 1995 Roland Corporation
d. 19	Grande Valse Brillante	F. Chopin	© 1995 Roland Corporation
d. 20	La prière d'une Vierge	T. Badarzewska	© 1996 Roland Corporation
d. 21	Course en Troïka	P. Tchaikovsky	© 1996 Roland Corporation
d. 22	To The Spring	E. Grieg	© 1996 Roland Corporation
d. 23	Valse, op.64-2	F. Chopin	© 1996 Roland Corporation
d. 24	Radetzky Marsch	J. Strauss	© 1996 Roland Corporation
d. 25	Träumerei	R. Schumann	© 1996 Roland Corporation
d. 26	Moments Musicaux III	F. Schubert	© 1996 Roland Corporation
d. 27	Prélude, op.28-15	F. Chopin	© 1996 Roland Corporation
d. 28	The harmonious blacksmith	G. Handel	© 1996 Roland Corporation
d. 29	Ungarische Tänze V	J. Brahms	© 1996 Roland Corporation
d. 30	Türkischer Marsch (Beethoven)	L. v. Beethoven	© 1996 Roland Corporation
d. 31	Nocturne No.2	F. Chopin	© 1996 Roland Corporation
d. 32	Frühlingslied	F. Mendelsshon	© 1996 Roland Corporation
d. 33	Präludium	J. S. Bach	© 1996 Roland Corporation
d. 34	Jägerlied	F. Mendelsshon	© 1996 Roland Corporation
d. 35	Menuet Antique	M. Ravel	© 1996 Roland Corporation
d. 36	Für Elise	L. v. Beethoven	© 1996 Roland Corporation
d. 37	Türkischer Marsch (Mozart)	W. A. Mozart	© 1996 Roland Corporation
d. 38	Ständchen	F. Schubert	© 1996 Roland Corporation
d. 39	Humoreske	A. Dvorjak	© 1996 Roland Corporation
d. 40	Blumenlied	G. Lange	© 1996 Roland Corporation
d. 41	Alpenglökkchen	T. Oesten	© 1996 Roland Corporation
d. 42	Menuett G dur (Beethoven)	L. v. Beethoven	© 1996 Roland Corporation
d. 43	Venezianisches Gondellied	F. Mendelsshon	© 1996 Roland Corporation
d. 44	Alpenabendröte	T. Oesten	© 1996 Roland Corporation

Song No.	Song Name	Composer	Copyright
d. 45	Farewell to the Piano	L. v. Beethoven	© 1996 Roland Corporation
d. 46	Brautchor	W. Wagner	© 1996 Roland Corporation
d. 47	Battle of Waterloo	W. Anderson	© 1996 Roland Corporation
d. 48	Wiener Marsch	C. Czerny	© 1996 Roland Corporation
d. 49	Le Coucou	L. C. Daquin	© 1996 Roland Corporation
d. 50	Menuett G dur (Bach)	J. S. Bach	© 1992 Roland Corporation
d. 51	Spinnerlied	A. Ellmenreich	© 1996 Roland Corporation
d. 52	Gavotte	F. Gossec	© 1996 Roland Corporation
d. 53	Heidenröslein	G. Lange	© 1996 Roland Corporation
d. 54	Zigeuner Tanz	H. Lichner	© 1996 Roland Corporation
d. 55	La Cinquantaine	G. Marie	© 1996 Roland Corporation
d. 56	Csikos Post	H. Necke	© 1996 Roland Corporation
d. 57	Dolly's Dreaming Awakening	T. Oesten	© 1996 Roland Corporation
d. 58	La Violette	L. Streabbog	© 1996 Roland Corporation
d. 59	Fröhlicher Landmann	R. Schumann	© 1996 Roland Corporation
d. 60	Sonatine op.36-1 (Clementi)	M. Clementi	© 1996 Roland Corporation
d. 61	Sonatine op.20-1 (Kuhlau)	F. Kuhlau	© 1996 Roland Corporation
d. 62	Sonatine No.5 (Beethoven)	L. v. Beethoven	© 1996 Roland Corporation
d. 63	Hungarian Rag: Hungarian Dance No. 5 Ragtime Arrangement For Solo Piano	J. Brahms/ Arranged by John Maul	© 1996 Roland Corporation
d. 64	Paganooogie Variation: Jazz Variation Based on "Caprice No. 24 in A Minor"	N. Paganini/ Arranged by John Maul	© 1998 Roland Corporation
d. 65	L'éveil del l'amour	Masashi & Kazuko Hirashita	© 2000 Roland Corporation

* All rights reserved. Unauthorized use of this material for purposes other than private, personal enjoyment is a violation of applicable laws.

DIGITAL PIANO

Date : Apr. 1, 2002

Model ep-760

MIDI Implementation Chart

Version : 1.00

Function...	Transmitted	Recognized	Remarks
Basic Channel Default Changed	1 1—16	1 1—16	
Mode Default Messages Altered	Mode 3 x *****	Mode 3 x	
Note Number : True Voice	15—113 *****	0—127 15—113	
Velocity Note ON Note OFF	O x 8n v=64	O x	
After Touch Key s Ch s	x x	x x	
Pitch Bend	x	x	
Control Change 6, 38 7 11 64 66 67 91 93 100, 101	O x x O O O O O O O	O O O O O O O O O	Data entry Volume Expression Hold 1 Sostenuto Soft Effect 1 (Reverb) Effect 3 (Chorus) RPN LSB, MSB
Prog Change : True Number	O (0...119) *****	O (0—127) 0...119	
System Exclusive	O	O	
System Common : Song Pos : Song Sel : Tune	x x x	x x x	
System Real Time : Clock : Commands	x x	x x	
Aux Message : All sound off : Reset all controllers : Local Control : All Notes OFF : Active Sense : Reset	x x x x O x	x O O O (123—127) O x	
Notes			

Mode 1 : OMNI ON, POLY

Mode 2 : OMNI ON, MONO

O : Yes

Mode 3 : OMNI OFF, POLY

Mode 4 : OMNI OFF, MONO

X : No

ep-760 Reference

Information

When you need repair service, call your nearest Roland Service Center or authorized Roland distributor in your country as shown below.

AFRICA

EGYPT

AI Fanny Trading Office
9, EBN Hagar A1 Askalany Street,
ARD El Golf, Heliopolis,
Cairo 11341, EGYPT
TEL: 20-2-417-1828

REUNION

Maison FO - YAM Marcel
25 Rue Jules Hermann,
Chaudron - BP79 97 491
Ste Clotilde Cedex,
REUNION ISLAND
TEL: (0262) 218-429

SOUTH AFRICA

**That Other Music Shop
(PTY) Ltd.**
11 Melle St., Braamfontein,
Johannesburg, SOUTH AFRICA

P.O. Box 32918, Braamfontein 2017
Johannesburg, SOUTH AFRICA
TEL: (011) 403 4105

Paul Bothner (PTY) Ltd.
17 Werdmuller Centre,
Main Road, Claremont 7708
SOUTH AFRICA

P.O. BOX 22032, Claremont 7735,
SOUTH AFRICA
TEL: (021) 674 4030

ASIA

CHINA

**Beijing Xinghai Musical
Instruments Co., Ltd.**
6 Huangmunchang Chao Yang
District, Beijing, CHINA
TEL: (010) 6774 7491

**Shanghai Xingtong Acoustics
Equipment CO., Ltd.**
5F, No.1500 Pingliang Road
New East Club Plaza, Shanghai,
CHINA
TEL: (021) 5580-0800

HONG KONG

**Tom Lee Music Co., Ltd.
Service Division**
22-32 Pun Shan Street, Tsuen
Wan, New Territories,
HONG KONG
TEL: 2415 0911

INDIA

Rivera Digitec (India) Pvt. Ltd.
409, Nirman Kendra Mahalaxmi
Flats Compound Off. Dr. Edwin
Moses Road, Mumbai-400011,
INDIA
TEL: (022) 498 3079

INDONESIA

PT Citra IntiRama
Jl. Cideng Timur No. 15J-150
Jakarta Pusat
INDONESIA
TEL: (021) 6324170

KOREA

Cosmos Corporation
1461-9, Seocho-Dong,
Seocho Ku, Seoul, KOREA
TEL: (02) 3486-8855

MALAYSIA

BENTLEY MUSIC SDN BHD
140 & 142, Jalan Bukit Bintang
55100 Kuala Lumpur, MALAYSIA
TEL: (03) 2144-3333

PHILIPPINES

G.A. Yupangco & Co. Inc.
339 Gil J. Puyat Avenue
Makati, Metro Manila 1200,
PHILIPPINES
TEL: (02) 899 9801

SINGAPORE

Swee Lee Company
150 Sims Drive,
SINGAPORE 387381
TEL: 846-3676

CRISTOFORI MUSIC PTE LTD

Blk 3014, Bedok Industrial Park E,
#02-2148, SINGAPORE 489980
TEL: 243 9555

TAIWAN

**ROLAND TAIWAN
ENTERPRISE CO., LTD.**
Room 5, 9fl. No. 112 Chung Shan
N.Road Sec.2, Taipei, TAIWAN,
R.O.C.
TEL: (02) 2561 3339

THAILAND

Theera Music Co., Ltd.
330 Verg NakornKasem, Soi 2,
Bangkok 10100, THAILAND
TEL: (02) 2248821

VIETNAM

Saigon Music
138 Tran Quang Khai St.,
District 1
Ho Chi Minh City
VIETNAM
TEL: (08) 844-4068

AUSTRALIA/ NEW ZEALAND

AUSTRALIA

**Roland Corporation
Australia Pty., Ltd.**
38 Campbell Avenue
Dee Why West, NSW 2099
AUSTRALIA
TEL: (02) 9982 8266

NEW ZEALAND

Roland Corporation Ltd.
32 Shaddock Street, Mount Eden,
Auckland, NEW ZEALAND
TEL: (09) 3098 715

CENTRAL/LATIN AMERICA

ARGENTINA

Instrumentos Musicales S.A.
Av. Santa Fe 2055
(1123) Buenos Aires
ARGENTINA
TEL: (011) 4508-2700

BRAZIL

Roland Brasil Ltda
Rua San Jose, 780 Sala B
Parque Industrial San Jose
Coba - Sao Paulo - SP, BRAZIL
TEL: (011) 4615 5666

COSTA RICA

**JUAN BANSBACH
Instrumentos Musicales**
Ave. J. Calle 11, Apartado 10237,
San Jose, COSTA RICA
TEL: 258-0211

CHILE

Comercial Fancy II S.A.
Rut.: 96.919.420-1
Nataliel Cox #739, 4th Floor
Santiago - Centro, CHILE
TEL: (02) 688-9540

EL SALVADOR

OMNI MUSIC
75 Avenida Norte y Final
Alameda Juan Pablo II,
Edificio No.4010 San Salvador,
EL SALVADOR
TEL: 262-0788

MEXICO

Casa Veerkamp, s.a. de c.v.
Av. Toluca No. 323, Col. Olivar
de los Padres 01780 Mexico D.F.
MEXICO
TEL: 668-0480

PANAMA

SUPRO MUNDIAL, S.A.
Boulevard Andrews, Albrook,
Panama City, REP. DE PANAMA
TEL: 315-0101

PARAGUAY

**Distribuidora De
Instrumentos Musicales**
J.E. Olear y ESQ. Manduvira
Asuncion PARAGUAY
TEL: (0512) 492-124

PERU

VIDEO Broadcast S.A.
Portinari 199 (ESQ. HALS),
San Borja, Lima 41,
REP. OF PERU
TEL: (01) 4758226

URUGUAY

Todo Musica S.A.
Francisco Acuna de Figueroa 1771
C.P.: 11.800
Montevideo, URUGUAY
TEL: (02) 924-2335

VENEZUELA

Musiland Digital C.A.
Av. Francisco de Miranda,
Centro Parque de Cristal, Nivel
C2 Local 20 Caracas
VENEZUELA
TEL: (212) 285-8586

EUROPE

AUSTRIA

Roland Austria GES.M.B.H.
Siemensstrasse 4, P.O. Box 74,
A-6063 RUM, AUSTRIA
TEL: (0512) 26 44 260

BELGIUM/HOLLAND/ LUXEMBOURG

Roland Benelux N. V.
Houtstraat 3, B-2260, Oevel
(Westerlo) BELGIUM
TEL: (014) 575811

DENMARK

Roland Scandinavia A/S
Nordhavnsvej 7, Postbox 880,
DK-2100 Copenhagen
DENMARK
TEL: (039)16 6200

FRANCE

Roland France SA
4, Rue Paul Henri SPAAK,
Parc de l'Esplanade, F 77 462 St.
Thibault, Lagny Cedex FRANCE
TEL: 01 600 73 500

FINLAND

**Roland Scandinavia As,
Filial Finland**
Lautasaarentie 54 B
Fin-00201 Helsinki, FINLAND
TEL: (9) 682 4020

GERMANY

**Roland Elektronische
Musikinstrumente HmbH.**
Oststrasse 96, 22844 Norderstedt,
GERMANY
TEL: (040) 52 60900

GREECE

STOLLAS S.A.
Music Sound Light
155, New National Road
Patras 26442, GREECE
TEL: (061) 43-5400

HUNGARY

Intermusica Ltd.
Warehouse Area 'DEPO' Pf.83
H-2046 Torokbalint, HUNGARY
TEL: (23) 511011

IRELAND

Roland Ireland
Audio House, Belmont Court,
Donnybrook, Dublin 4,
Republic of IRELAND
TEL: (01) 2603501

ITALY

Roland Italy S. p. a.
Viale delle Industrie 8,
20020 Arese, Milano, ITALY
TEL: (02) 937-78300

NORWAY

**Roland Scandinavia Avd.
Kontor Norge**
Lilleakerveien 2 Postboks 95
Lilleaker N-0216 Oslo
NORWAY
TEL: 273 0074

POLAND

P. P. H. Brzostowicz
UL. Gibraltaraka 4,
PL-03664 Warszawa POLAND
TEL: (022) 679 44 19

PORTUGAL

**Tecnologias Musica e Audio,
Roland Portugal, S.A.**
Cais Das Pedras, 8/9-1 Dto
4050-465 PORTO
PORTUGAL
TEL: (022) 608 00 60

ROMANIA

FBS LINES
Piata Libertatii 1,
RO-4200 Gheorgheni
TEL: (095) 169-5043

RUSSIA

MuTek
3-Bogatyrskaya Str. 1.k.lj
107 564 Moscow, RUSSIA
TEL: (095) 169 5043

SPAIN

**Roland Electronics
de España, S. A.**
Calle Bolivia 239, 08020
Barcelona, SPAIN
TEL: (93) 308 1000

SWEDEN

**Roland Scandinavia A/S
SWEDISH SALES OFFICE**
Danvik Center 28, 2 tr.
S-131 30 Nacka SWEDEN
TEL: (08) 702 0020

SWITZERLAND

**Roland (Switzerland) AG
Musitronic AG**
Gerberstrasse 5, Postfach,
CH-4410 Liestal, SWITZERLAND
TEL: (061) 927-8383

UKRAINE

TIC-TAC
Mira Str. 19/108
P.O. Box 180
285400 Munkachevo, UKRAINE
TEL: (03131) 414-40

UNITED KINGDOM

Roland (U.K.) Ltd.
Atlantic Close, Swansea
Enterprise Park, SWANSEA
SA7 9FJ,
UNITED KINGDOM
TEL: (01792) 700139

MIDDLE EAST

BAHRAIN

Moon Stores
No.16, Bab Al Bahrain Avenue,
P.O.Box 247, Manama 304,
State of BAHRAIN
TEL: 211 005

CYPRUS

Radex Sound Equipment Ltd.
17, Diagonou Street, Nicosia,
CYPRUS
TEL: (02) 66-9426

IRAN

MOCO, INC.
No.41 Nike St., Dr.Shariyati Ave.,
Roberoye Cerahe Mirdamad
Tehran, IRAN
TEL: (021) 285-4169

ISRAEL

**Halilit P. Greenspoon &
Sons Ltd.**
4 Retzif Ha'aliya Hashnya St.
Tel-Aviv-Yafa ISRAEL
TEL: (03) 6823666

JORDAN

AMMAN Trading Agency
245 Prince Mohammad St.,
Amman 1118, JORDAN
TEL: (06) 464-1200

KUWAIT

Easa Husain Al-Yousifi
Abdullah Salem Street,
Safat, KUWAIT
TEL: 243-6399

LEBANON

A. Chahine & Fils
Gerge Zeidan St., Chahine Bldg.,
Achrafieh, P.O.Box 16-5857
Beirut, LEBANON
TEL: (01) 20-1441

QATAR

**Al Emadi Co. (Badie Studio
& Stores)**
P.O. Box 62,
Doha, QATAR
TEL: 4423-554

SAUDI ARABIA

**aDawlah Universal
Electronics APL**
Corniche Road, Aldossary Bldg.,
1st Floor, Alkhobar,
SAUDI ARABIA

P.O.Box 2154, Alkhobar 31952
SAUDI ARABIA
TEL: (03) 898 2081

SYRIA

**Technical Light & Sound
Center**
Bldg. No. 47,
Khaled Ebn Al Walid St.
Damascus, SYRIA
TEL: (011) 221-1230

TURKEY

**Barkat muzik aletleri ithalat
ve ihracat Ltd Sti**
Siraselviler Caddesi Siraselviler
Pasaji No:74/20
Taksim - Istanbul, TURKEY
TEL: (0212) 2499324

U.A.E.

**Zak Electronics & Musical
Instruments Co. L.L.C.**
Zabeel Road, Al Sherouq Bldg.,
No. 14, Grand Floor, Dubai, U.A.E.
TEL: (04) 3360715

NORTH AMERICA

CANADA

Roland Canada Music Ltd.
(Head Office)
5480 Parkwood Way Richmond
B. C., V6V 2M4 CANADA
TEL: (0604) 270 6626

Roland Canada Music Ltd.

(Toronto Office)
Unit 2, 109 Woodbine Downs
Blvd, Etobicoke, ON
M9W 6Y1 CANADA
TEL: (0416) 213 9707

U. S. A.

Roland Corporation U.S.C.
5100 S. Eastern Avenue
Los Angeles, CA 90040-2938,
U. S. A.
TEL: (323) 890 3700

As of January 1, 2002 (Roland)

 Roland®

K6018479

UPC

K6018479



10991

Roland